N Scale UNITRACK

~~ Amherst 2005 ~~



The overall table size of this layout is 4' 6" X 2' 6". It is a variation of a basic two-track oval but with some interesting elements. The bridges, double crossover and inside yards all add realism exponentially to this little layout.

It is suggested this layout to be built on 2" foam insulation. Cut down into the foam to make the pond and creek. Slightly elevate the outermost curve on the right end using Woodland Scenics foam risers for appearance of varied topography.

Operating into inner "yard" tracks or operation under DCC may require additional Feeder Tracks and/or #24-818 Terminal Unijoiners.

It is recommended the layout be operated with (2) #22-014 KATO Power Packs, although other power packs can also be used. If using power pack from another manufacturer, (2) #24-843 Adapter Cords are recommended for simplified connection between pack and Feeder Tracks.

To operate turnouts and Double Crossover electrically, use (6) #24-840 Turnout Control Switches. (1) #24-842 DC Converter will also be required if not using KATO Power Pack. #24-841 Turnout Extension Cords may also be necessary.

Item #	Description	# Pieces
20-000	248mm Straight Track	4 (1 pkg)
20-010	186mm Straight Track	4 (1 pkg)
20-020	124mm Straight Track	5 (2 pkgs)
20-040	62mm Straight Track	1 (1 pkg)
20-041	62mm Feeder Track	2 (2 pkgs)
20-04X	Bumper	5 (3 pkgs)
20-091	Track Assortment Set	(1 set)
	45mm from 20-091	2
	29mm from 20-091	1
20-100	R249-45 Curved Track	8 (2 pkgs)
20-110	R282-45 Curved Track	8 (2 pkgs)
20-111	R282-15 Curved Track	3 (1 pkg)
20-120	R315-45 Curved Track	4 (1 pkg)
20-150	R718-15 Curved Track	4 (1 pkg)
20-202	#6 Ele. Turnout Left	2 (2 pkgs)
20-203	#6 Ele. Turnout Right	4 (4 pkgs)
20-210	Double Crossover	1 (1 pkg)
20-220	#4 Ele. Turnout Left (includes accessory pieces)	1 (1 pkg)
20-431	Truss Bridge	1 (1 pkg)
20-435	Double Track Truss Bridge	1 (1 pkg)

Some pieces from multi-piece packages will be surplus. Indicated structures in plan are suggestion only.

br011305